



# Wireless Controller for Low Voltage Hoist

## Instruction Manual

Models:

**GMC12-WLV-3H24,**

**GMC12-WLV-12H6**

version 1.0 since 3 February 2020

**GMC8-WLV-2H24**

### **ATTENTION!**

This instruction manual contains important information about the installation and the use of the equipment. Please read and follow these instructions carefully.

Always ensure that the power to the equipment is disconnected before opening the equipment or commencing any maintenance work.

# Safety information

## ***IMPORTANT INSTRUCTIONS***

All safety and operating instructions should be read before the equipment is installed or operated.

## ***IMPORTANT SAFETY INFORMATION***

The following general safety precautions have to be observed during all phases of operation, service, and the repair of this equipment. Failure to comply with these precautions or with specific warnings in this manual violates safety standards of design, manufacture, and the intended use of this equipment.

### ***Do not operate in an explosive atmosphere!***

Do not operate this equipment in the presence of flammable gases or fumes. Operation of any electrical instrument in such an environment constitutes a definite safety hazard.

### ***Water, moisture, heat and humidity***

Do not operate this equipment near water or in areas with wet floors or in high humidity atmosphere, where condensation forms on the equipment. It should never be placed near or over a heat register or other source of heated air and it should not be installed or operated without proper ventilation.

# Functions and Control

Motor Controller has been designed to control from 1 to 12 electrically compatible motors, either separately or simultaneously – controlled via switches located on front panel or wireless remote/pendant. Optionally you can link GO/STOP button by link connector.

Each device is equipped with unique APA /Automatic Phase Align/ module that guarantees that on any alignment of input phases the motors will move in the correct direction. If any line wire is disconnected, the hoist controller stops to ensure safe operation. Unit is also equipped with AVM /Automatic Voltage Metering/ module. This module checks the main voltage for AC400V +20% and the star configuration. If there is any problem with the main voltage, you're notified, and unit will not run any hoist.

Unit will not work when:

- One phase is missing
- Under-voltage is present on lines
- Over-voltage is present on lines

All electrical components carry their own individual cSA/UL, CE and comply with European Directives. The components are housed in robust steel 19" rack casing with powder coating. Complete unit complies with the CE according to the Certification of conformity attached to this manual.

## Operation

The motors/hoists connected with the GMCseries controller can be activated individually or simultaneously using the GO switch located on the front panel or wireless remote. Units can be optionally linked together to create bigger systems.

## How to start

- Connect the CEE32/5p plug to the AC400V +20% power supply – turn the key to ON position. When the main power is OK, the power LED will light green, otherwise the unit is OFF. Check phase voltages, frequency and contact the manufacturer if help is needed.
- Connect the plugs for the electric hoists to the output sockets.
- Check that the emergency STOP mushroom on the device is not engaged or any other linked device in system.

Move lever on the front panel or WMC remote corresponding to each motor to the required position:


- UP - Lever in upper position
  - STAY – Lever in middle position
  - DOWN - Lever in lower position
- Pushing the GO button will activate the motors to move simultaneously
  - Releasing the GO button will stop the movement of the motors simultaneously.
  - When the device is not being used, it is highly recommended to turn it OFF by the key located on the front panel.

## To Move a single/several hoist(s):

- Set the UP/DOWN toggle switch for certain motor to the desired direction. The associated LED should light green for UP, or red for DOWN direction
- Hold the GO button until the motor is moved the desired height, then release.

## WMCseries remote controller

WMCseries remote allows control of the device via wireless connection.



## STOP:


This latching pushbutton switch turns the Hoist Control system off. Once the STOP button has been pressed, it locks the unit to OFF position and must be rotated clockwise and released before disengaging.

## GO:

This pushbutton switch turns the selected channels of Hoist Control system ON, when the unit is active. Once the GO button has been pressed, the energizing of the hoists is ON. The backlight of GO button in local mode on the Base unit is ON only when one or more direction switches are in active position /UP or DOWN/.

## DIRECTION SWITCHES:

They allow changing of the direction of movement for each motor/hoist separately:



## BATTERY STATUS LED:



Battery status LED indicator:

- Green: 100-90%
- Orange: 90-10%
- Red: 10%
- Red + beep: 5%

## REMOTE STATUS LED:



Status LED indicator of WMC remote unit:

- Green: Power ON
- Green blinking: Power ON – SLEEP - move the direction switch or press GO button to resume from sleep. This status becomes after 3 minutes of inactivity.
- Orange: Indicates direction switch activity
- Red: GO button is pressed – sending commands to the Base unit

## Link of WMC remotes:

Up to two WMC remotes can be linked together to group the operation of STOP and GO buttons. To link two WMC units, 5-pin miniXLR cable with custom wire connection is needed.

**Never use 1:1 cable – remotes can be destroyed.**

When WMC remotes are linked, the GO and STOP buttons are linked – so press of any STOP and GO button will work for both linked devices.




## Link of Base WLV units:

Up to 30 Base units can be linked via link connector located on the front panel. To link two WMC units, 5-pin DMX data cable is needed.

**Due to safety requirements, the link function works only in LOCAL / LINK MODE of the controller.**

# GMC12-WLV series Base unit

## GMCseries front panel



### Hoist protection:

- GMC12: Each three hoists are protected by single C16/3p MCB

### Power key switch positions:

- OFF: Power OFF /Only battery charger is active in this state/
- PICKLE: Power to the hoist is enabled
- AUTO: Power to the hoist is enabled when GO command is received

### GROUP STOP key switch positions:

- OFF: Trip of any breaker or mains GFI breaker will not cause E-STOP
- ON: Trip of any breaker or mains GFI will cause E-STOP of the unit

### MODE key switch positions:

- Local / LINK: Device works via local control or via network in linked operation
- Radio Remote: Device is controlled via wireless radio remote

### RESET:

RESET button works for the SIL3 E-STOP relay reset. RESET needs be pressed every time after the unit is turned ON, the E-STOP mushroom has been pressed or when the GROUP STOP has been activated.

## **EMERGENCY STOP:**

E-STOP is a red color mushroom. Once the E-STOP button has been pressed, it locks the unit into active position and must be rotated clockwise and released before disengaging. After engaging the E-STOP button, the RESET button needs to be pressed to reset the system.

## **GO:**

This green pushbutton turns the selected channels of Hoist Control system ON when is active. Once the GO button has been depressed, the energizing of the hoists is turned OFF.

## **DIRECTION SWITCHES:**

They allow changing the direction of movement for each motor/hoist separately or in groups. LED close to the switch indicates the movement direction.

## **Charger status LED:**

Status LED of charger located on the front panel is

- Green: Battery is fully charged
- Green blinking: Battery is charged to 90% or greater capacity
- Orange blinking: Not in rapid mode – waiting to be charged
- Red: Battery is in rapid charge mode
- Red blinking: Battery is ultra-rapid charge mode
- No LED: Battery is not inserted

## **Limit STOP input:**



LIMIT STOP connectors for external E-STOP from NLP device.

## **Link input:**

Link input for linking of GMC units.



# GMCseries rear panel



## **MAINS:**

Mains input on 1.5m cable + fuse for mains transformer T2.5A.

## **AUX output:**

AUX output for additional AC230 powered devices. Protected by C16/1p breaker on the front panel.

# **Output connectors wiring**

## **Harting 24 Female**

Pin	Function
1	L1
2	L1
3	L2
4	L2
5	L3
6	L3
7	M2 down
8	M2 common
9	M2 UP
10	M4 down
11	M4 common
12	M4 UP
13	L1
14	L1
15	L2
16	L2
17	L3
18	L3
19	M1 down
20	M1 common
21	M1 UP
22	M3 down
23	M3 common
24	M3 UP
Body	PE

## Remote/link connector

### Neutrik NC5-MAH/FAH

Connectors are used for a link operation of LV unit or for an additional digital remote CMC-xx-DIGI connection. Up to 30 units can be linked. They are then controlled via one GO and E-STOP button in the local operation mode.

Pin	Function	note
1	<b>Data CMN</b>	<i>Data Common</i>
2	<b>Data -</b>	<i>Data Minus</i>
3	<b>Data+</b>	<i>Data Plus</i>
4	<b>DC1</b>	<i>Power supply for CMC DC12-36V</i>
5	<b>DC2</b>	<i>Power supply for CMC DC12-36V</i>



## Loadcell E-STOP connector

### Neutrik NC4-FAH

Pin	Function	note
1	<b>DC24-36V</b>	Connected to 3
2	<b>Active 1</b>	Active line 1
3	<b>DC24-36V</b>	Connected to 1
4	<b>Active2</b>	Active line 2



Both safety lines are separate and NO /normally open/.

Load-cell E-STOP activation contacts must be in NC /normally closed/ state for E-STOP activation.

To reset the load-cell E-STOP function, please cycle the E-STOP mushroom on the device.

## Technical data

- Mains input AC400V +-20% 50/60Hz
- Mains Plug: CEE32A/5p

## Protections and Safety:

- Short-circuit protection of group of hoists by automatic circuit breakers C20A
- APA – Automatic Phase Align
- AVM – Automatic Voltage Metering
- Double mechanical blocking contactors
- Double - Recessed Emergency STOP with SIL3 certification

## Housing:

- Body: 1.5mm steel housing with gray powder coating
- Front panel: 3mm steel housing with gray powder coating

## Dimensions /W x D x H/:

GMC12-WLV-3H24: 8U box

## Warranty

GMCseries hoist controller comes with a 2-year manufacturer's warranty. For extended warranty conditions, please contact the manufacturer at [sales@srs-group.com](mailto:sales@srs-group.com).

The warranty covers the original factory installed components of the controller and their correct functioning.

The warranty voids if:

- any part or replacement components is installed or modified without authorization from the manufacturer and/or the internal circuit is tampered or modified, and/or the controller is operated outside normal use conditions
- electrical power supply does not conform or there is a connection error or mechanical damage of the controller, including overload and improper use.

The manufacturer always helps you to repair your unit.

# Declaration of conformity

## DECLARATION OF CONFORMITY

According to guide lines **89/336 EEC** and **92/31 EEC**, **90/337 CEE Annex II A**:

**Name of producer:** SRS Group s.r.o.

**Address of producer:** Rybnicna 38/B, SK- 83107 Bratislava, Slovak Republic  
[www.srs-group.com/sales@srs-group.com](http://www.srs-group.com/sales@srs-group.com), +421252661800

*Declares that the product*

**Name of product: GMCseries** hoist controller: GMC12-WLV + GMC8-WLV + variants

### Types:

MC12-WLV-3H24: Low voltage hoist/motor controller

*Corresponds with following harmonized standards:*

**Safety:** EN 60065  
EN 60950  
EN 60204-1  
EN 13850  
EN 12100-2  
AS/NZS 3820

**EMC:** EN55103-1, resp. EN55103-2


**And**

*Is in compliance with following requirements:*

**Machinery directive:** 2006/42/EC

**Low Voltage directive:** 2006/95/EC

Bratislava, 04 May 2016



Robert Sloboda





Copyright 2020 SRS Group s.r.o. | Specifications subject to change without notice.  
Document:GMC12-WLV-3H24\_en\_manual\_M237 | Version1.0| Actual as of: 3 February 2020



**SRS Group s.r.o.**

Rybnicna 38/B | 831 07 Bratislava | Slovakia

Phone: +421 2 32 661 800

Email: [sales@srs-group.com](mailto:sales@srs-group.com) | [www.srs-group.com](http://www.srs-group.com)

