# DST4WH (PRO) Wireless DMX /AC Power Splitter/Booster /Transceiver

The DST4WH is a handy 4-channel portable splitter / booster of the DMX signal and AC power and receiver of the W-DMX signal. The DST4WH PRO version also works as a transceiver of the W-DMX signal. Every output features LED indication of the DMX status and is optically isolated up to 1000V. The unit also provides a true output for easy daisy-chaining of other DMX devices.

Unit can be easily mounted on truss using SRS straps (included) or M10 clamp (not included). The DST4WH comes with 3- or 5-pin XLR connectors or a combination of them.

# Power supply

AC 100-255V / 50-60Hz, 5W

### Operating temperature

-20 °C to +40 °C

### Housing

Aluminium; gray powder coating

# Dimensions & Weight

234 x 154 x 62mm, 1.7kg

### Warrantv

Life-time











# **DST4WH (PRO) features:**

- Over-voltage protection of the DMX inputs & outputs
- 4 optically isolated/boosted outputs
- LED indication of the DMX line
- Neutrik connectors
- AC 20A to 4x PowerCon AC power distributor (max. 20A)
- Wireless DMX from Wireless Solution or LumenRadio
- M10 thread for C-CLAMP

### DMX input/output:

- 4x USITT DMX 512
- ESD protected to 10kV
- Each one optically isolated up to 1000V
- Each one equipped with a separate line driver
- DMX line indication status with two data LEDs

# XLR 3-/5-pin connector (Neutrik®):

Pin 1 Data CMN





Pin 4, 5 not connected







DST4WH-(PRO)\_en\_datasheet\_M316







